

# Template Guide Bushing and Adaptor Selection Chart

## How To Use This Chart

- A) Locate the name of the router maker in Column A
- B) Locate the model of the router in Column B
- C) Locate the required adaptor for your router in Column C
- Order Leigh guide bushing adaptors, **red part numbers**, from Column C
  - Order Bosch guide bushing adaptors, green part numbers, available from Leigh or your Bosch dealer, from Column C
  - Part numbers in black, in column C, must be ordered from the router manufacturers dealer
- D) Guide bushings in Columns D, E & F fit all adaptors listed and may be ordered if required. See notes below.

◆ The e7 guide bushing is supplied with all Leigh dovetail jigs. Order only if you require a replacement.

● The e8, 1/2" OD guide bushing is supplied with all F3, F18 and F24 Finger Joint Templates and is used **only** with these templates. Order only if you require a replacement.

The e10 is also used on F3, F18 and F24 Finger Joint Templates and is supplied with the templates. Order only if you require a replacement

▲ 5/8" OD guide bushings (e10 and 716TP) are used with 1/2" shank router bits on D4R Pro, D4R, D4, D3 and D1258(R) jigs. Order only if you are using 1/2" shank router bits.

★ Leigh adaptors 702, 702R, and 703 may require a small lug to be drilled out to use the e7, e8 and e10 guide bushings. Instructions supplied with the adaptor.

■ Mafell - Rework the adaptor slightly

**Note:** adaptor mounting screws are provided with router

**Note:** Ideal barrel depth is 1/4" to 9/32" (6mm to 8mm) below the router base. Other manufacturer's guide bushings may require careful cutting to length. All Leigh guide bushings have 9/32" long barrels.

**Note:** Column G indicates compatibility with the VGS Variable Guide Bush System. The VGS is used **only** on Leigh Isoloc Templates and the Leigh F1 and F2 Finger Joint Templates. The VGS is not required for Dovetail operations.

### Adaptors For Router Tables

Leigh guide bushings, including the Leigh eBushes, are based on the industry standard 1-3/8" 2-piece design. Most router tables have adaptors that accept these standard guide bushings. If your router table does not have a suitable adaptor, please check with the router table manufacturer.

	A	B	C	D	E	F	G
	Router Maker	Router Model	Leigh or Router Maker's Adaptor	7/16" OD Guide Bushing ◆	1/2" OD Guide Bushing ●	5/8" OD Guide Bushing ▲	Works With VGS
	AXMINSTER WHITE	AW635R, AW127R	710	711TP or e7	e8	716TP or e10	YES
		All Professional, HD 1250, RP400K, 7614	No adaptor required	711TP or e7	e8	716TP or e10	YES
	BLACK & DECKER	6200	720673-00	711TP or e7	e8	716TP or e10	YES
		SR100, 7AEE, KW780 series, KW800, KW850	710	711TP or e7	e8	716TP or e10	YES
		90140, 90098, 90088	No adaptor required		82855	82854	NO
		90085, 90150, 90300, 90303, 90305, 91264			82859	82864	NO
		1600, 1601, 1602, 1603, 1604, 1606, B1350	2 610 906 290	711TP or e7	e8	716TP or e10	YES
	BOSCH	ROUTERS PRODUCED AFTER mid 2010: 1613AEVS, 1617/EVS, 1618/EVS and MR23EVS series, sold in North America require Bosch Adaptors RA1100 and RA1126.	RA1100 Template Adaptor and RA1126 Quick Change Adaptor required	711TP or e7	e8	716TP or e10	YES
		ROUTERS PRODUCED BEFORE mid 2010: 1613AEVS, 1617/EVS, 1618/EVS, 1619EVS POF800ACE, POF1400ACE, POF1100AE, POF1200AE, GOF900ACE, GOF1300ACE, GOF900CE, GOF2000CE, GOF1200, GMF1400, B1450	RA1100	711TP or e7	e8	716TP or e10	YES
		1611, 1611EVS, 1615, 1615EVS, B1550, GOF1600, GOF1700ACE	702*	711TP or e7	e8	716TP or e10	YES
	CMT	1E	702R*	711TP or e7	e8	716TP or e10	YES
		All non-plunge models	Aftermarket Base Plate Required	5-piece set from Sears USA: Order no.0925973 or 3-piece set from Sears Canada: Order no.0900970704.			NO
		135275070 Plunge		See Skil 1823 or 1835			
	CRAFTSMAN SEARS	Other plunge models	702*	711TP or e7	e8	716TP or e10	YES
		MD11 Plunge & Fixed Base, MD9.5 Plunge Base	No adaptor required	711TP or e7	e8	716TP or e10	YES
		DW610, DW616, DW618	No adaptor required	711TP or e7	e8	716TP or e10	YES
		DW613, DW615(UK)	710	711TP or e7	e8	716TP or e10	YES
		DW614, DW615, DW621, DW624, DW625 and DW626	North America Only Adaptor supplied w/router	711TP or e7	e8	716TP or e10	YES
	DeWalt	DW621K & DW626 outside N. America	706R	711TP or e7	e8	716TP or e10	YES
		DW625 Type 1, 2, 3, 5 outside N. America	702*	711TP or e7	e8	716TP or e10	YES
		DW624 & DW625 Type4 outside N.America, DW625EK	702R*	711TP or e7	e8	716TP or e10	YES
		OF15, OF15E, OF97, OF97E	706R*	711TP or e7	e8	716TP or e10	YES
		MOF68, MOF69, MOF96, MOF96E	710	711TP or e7	e8	716TP or e10	YES
		MOF131, MOF177 Type 1, 2 & 3	702*	711TP or e7	e8	716TP or e10	YES
		MOF177 Type 4, MOF177EK	702R*	711TP or e7	e8	716TP or e10	YES
		2720, 2721, 3328	No adaptor required	711TP or e7	e8	716TP or e10	YES
		3303, 3304	E09600 or 761 270-00	711TP or e7	e8	716TP or e10	YES
		3337, 3338, 3339	702*	711TP or e7	e8	716TP or e10	YES
	ELU	RT1800	Adaptor supplied w/router	711TP or e7	e8	716TP or e10	YES
		OF1E, OF2E, OF650, OF900E, OF1000, OF1010E	704R	711TP or e7	e8	716TP or e10	YES
		OF2000, OF2000E	705R	711TP or e7	e8	716TP or e10	YES
		OF1400 North America	Adaptor supplied w/router	711TP or e7	e8	716TP or e10	YES
		OF1400 Outside North America	493566	711TP or e7	e8	716TP or e10	YES
		OF2200	494627 - O-Ring may be required to keep guidebush centered	711TP or e7	e8	716TP or e10	YES
	FLEX	ALL	No adaptor required	711TP or e7	e8	716TP or e10	YES
	FREUD	FT1700(2), FT2000, FT2200, FT3000	721	711TP or e7	e8	716TP or e10	YES
		TR8, TR12, FM8, M8, M12 Series	325211 or 703*	711TP or e7	e8	716TP or e10	YES
	HITACHI	M12VC, KM12SC, KM12VC	No adaptor required	711TP or e7	e8	716TP or e10	YES
		M12SA2, M12V2	325224	711TP or e7	e8	716TP or e10	YES
	MAFELL	LO65E	702*	711TP or e7	e8	716TP or e10	YES
		RP1801, RP2301FC, 3612C Europe Qk.Fit Base	721	711TP or e7	e8	716TP or e10	YES
		3600, 3606, 3608, 3612, 3612B, 3612BR, 3612C N. America, 3620, 3621, RP0900K	703	711TP or e7	e8	716TP or e10	YES
		3601B	321 493-1	711TP or e7	e8	716TP or e10	YES
		RP0910, RP1110C	706R	711TP or e7	e8	716TP or e10	YES
		RF1100, RF1101, RD1100, RD1101, RP1101	No adaptor required	711TP or e7	e8	716TP or e10	YES
	METABO	OF1612, OFE1812	704R	711TP or e7	e8	716TP or e10	YES
		5615, 5616, 5619	49-54-1040	711TP or e7	e8	716TP or e10	YES
	MILWAUKEE	5625	49-54-1026	711TP or e7	e8	716TP or e10	YES
		5670	No adaptor required	711TP or e7	e8	716TP or e10	YES
	PERLES	OF808 Series, OFE 6990	710	711TP or e7	e8	716TP or e10	YES
	PORTER CABLE (ROCKWELL)	ALL	No adaptor required or adaptor supplied w/router	711TP or e7	e8	716TP or e10	YES
	POWER DEVIL	All	710	711TP or e7	e8	716TP or e10	YES
	RIDGID	R2930	Not Available From Leigh				
		R30, R50, R150, R151, RE155, R500, R501, R502	703*	711TP or e7	e8	716TP or e10	YES
		R600, R601, RE600, RE601	702*	711TP or e7	e8	716TP or e10	YES
		R160, R161, R162, R163K, R165, R170, R175, RE175, R180, R180PL, R181, R185, ERT1150	706R	711TP or e7	e8	716TP or e10	YES
		1823 or 1835	91803	711TP or e7	e8	716TP or e10	YES
		SK1810, 1815, 1820, 1825	RAS140	711TP or e7	e8	716TP or e10	YES
		All others	No adaptor required	11592		71021	NO
		T3, T4	710	711TP or e7	e8	716TP or e10	YES
		T5, T9	710	711TP or e7	e8	716TP or e10	YES
		T10, T11- UniBase required	710	711TP or e7	e8	716TP or e10	YES
	TRITON	TRC001, TRA001	TGA006 (or 704R)	711TP or e7	e8	716TP or e10	YES
		MOF001	TRA359	711TP or e7	e8	716TP or e10	YES
	WEGOMA	OF850 SERIES	710	711TP or e7	e8	716TP or e10	YES